Quick Guide – *OpenScape Mobile Client*

Working with Contacts

How to call contacts or edit contact entries:

Select from the **Contacts** view:

- **Default**, showing all contacts.
- ***<Group name>***, showing the contacts who are assigned to this group

How to call a contact:

- Open the desired contact group.
- Open the contact's context menu.
- Select ***Call***. The dialog for making calls opens.
- Select a phone number of the contact under **Number**.
- Select under **Call me on my device** the device from which you want to make the call.

How to view contact data:

- Open the desired contact group.
- Open the contact's context menu.
- Select ***Open***. The contact data is displayed.

How to create a new contact:

- Open the desired contact group.
- Open the contact's context menu.
- Select ***New contact*** or ***Manual Input.*** The **New Contact** dialog opens.
- In case of an *OpenScape UC Application* contact: Enter the user ID.
- In case of a manual input: Enter the contact data.
- Push ***OK*** or the return key.

The new contact data are saved.

How to create a new contact group:

Select from the **Contacts** view:

- ***New group***.
- Enter a group name.

How to add a contact to a group:

- Select the relevant contact from the **Contacts** view.
- Assign the contact to the desired group via the ***Add to group*** context menu.

How to edit a contact:

- Open the desired contact group.
- Open the contact's context menu.
- Select ***Edit***. The **Edit Contact** dialog opens.
- Edit the contact data.
- Push ***OK*** or the return key.
- The contact data is changed.

How to select several contacts:

- Open the desired contact group.
- Open the contact's context menu.
- Choose ***Select***.
- Repeat the process for further contacts.

After you have selected several contacts:

- ***Conference***: Starts an ad-hoc conference.
- ***Delete***: Deletes the selected contacts.
- ***Deselect***: Cancels a selection.
- ***Deselect All***: Cancels the selection of all entries.

How to delete a contact:

- Open the desired contact group.
- Open the contact's context menu.
- Select ***Delete***.
- The contact is removed from the contact list.

Finding Contacts

Access **Find Contact**:

- Enter the contact's first or second name or the initials. A hit list is displayed.

Context menu features:

- ***Add***: Adds the contact to the private address book.
- ***Call contact***: Calls the contact directly.
- ***Open***: Lets you see the contact's details.
- ***Find contact***: Starts a new contact search.

OpenScape UC Application V3
Copyright © 2011 Siemens Enterprise Communications GmbH & Co. KG
Siemens Enterprise Communications GmbH & Co. KG is a Trademark Licensee of Siemens AG
A31003-S5030-U119-3-7619
www.siemens-enterprise.com

Journal

Accessing the **call journal**:

- Select **Journal** in the contact view. The last 20 calls (inbound, outbound and missed) are displayed.

Context menu features:

- ***Call***: Choose a phone number or a name and select ***Call*** to initiate a call.
- ***Delete***: Removes entries from the journal.
- ***Select***: To mark one or several journal entries. You can then use the following options:

  Delete: Deletes the selected entries.

  Deselect: Cancels a selection.

  Deselect All: Cancels the selection of all entries.
- ***Back:*** Via this option you return to the contact view.

Devices

Accessing the **device list**:

- Select **Devices** in the contact view. The device list is displayed.

Context menu features:

- ***Select as Preferred Device:*** Select a device to configure it as your preferred device.
- ***New:*** Creates a new terminal device. The **New Device** dialog opens.
- ***Edit:*** Edits an existing device. The **Edit Device** dialog opens.
- ***Delete:*** Removes the selected device from the device list.
- ***Select:*** Marks one or several devices. You can then use the following options:

  Delete, to remove selected devices.

  Deselect, to cancel selecting a device.

  Deselect all, to cancel selecting all devices.
- ***Back:*** Via this option you return to the contact view.

Conferences

Accessing **conferences**:

- Select ***Conferences*** in the contact view. The list that contains all the conferences you have created is displayed.
- Active conferences
- Inactive conferences

Context menu features:

- ***Open***: Displays the conference details.
- ***Start conference***: Opens a dialog for starting the conference.

Via the context menu of the single conference members:

- Changing the dial-in status (member dials in himself/member is called).
- ***Back:*** Via this option you return to the contact view.

Updating Data

How to update data:

- Select **Refresh** in the contact view. Your data on the Mobile Client are synchronized with those stored on the server.

OpenScape UC Application V3
Copyright © 2011 Siemens Enterprise Communications GmbH & Co. KG
Siemens Enterprise Communications GmbH & Co. KG is a Trademark Licensee of Siemens AG
A31003-S5030-U119-3-7619
www.siemens-enterprise.com

Call

How to call any subscriber:

- Select **More... > Call** in the contact view.
- Enter the phone number.
- Specify the device from which the call is to be made.
- Push **OK**.

The call is being initiated.

Transferring an active Call

How to transfer an active call:

- Select in the contact view **More... > Handover active call**.
- Select the call to be transferred via the phone number or the associated name.
- ***Handover to***: Enter the extension number in this field.
- Push ***OK***.

The call is being transferred.

Note: The feature ***Handover to*** can only be used if it is supported by your terminal device as well as your provider.

Set Status

How to set your presence status:

- Select **More... > Set Status** in the contact view.
- Select the desired status.
- Complete the selection with the trackball or the return key.

The selected presence status is shown at the bottom margin of the display.

Set Rule

How to activate/deactivate a routing rule:

- Select **More... > Set Rule** in the contact view. The available rules are displayed. The active rule is indicated with an asterisk.
- ***How to deactivate a rule***: Select the rule and undo the activation.
- ***How to activate a new rule***: Select the new rule and activate it.

Subscriptions (*iPhone* und *Android*)

Set Subscriptions to display your presence- and telephone state:

- Select in the contact view **Subscriptions**. (*iPhone*: **More... > Subscriptions)**
- Select ***Pending***, ***Accepted*** or ***Blocked*** subscriptions.
- Select ***Accept subscription***, ***Block subscription*** or ***Reject subscription***.

Setting User Information

In the contact view select **More... > Settings**. You can invoke the following features:

- ***User information***:
  - ***Time zone settings***:
    1. Make a selection under ***Current Timezone***
    2. Specify a location under ***Location***
    3. Make an explanatory entry under ***Note*** (becomes visible with the presence information)
    4. Push ***OK*** or the return key to confirm entries.
  - ***Error report***:
    Opens a list that indicates errors.
  - ***About***:
    Displays the version number and license information.
- ***Options***:
  Auto Refresh (On/Off)

Closing the Mobile Client

Select **Exit in the contact view.**

The information provided in this document contains merely general descriptions or characteristics of performance which in case of actual use do not always apply as described or which may change as a result of further development of the products. An obligation to provide the respective characteristics shall only exist if expressly agreed in the terms of contract. Availability and technical specifications are subject to change without notice.
OpenScape, OpenStage and HiPath are registered trademarks of Siemens Enterprise Communications GmbH & Co. KG.
All other company, brand, product and service names are trademarks or registered trademarks of their respective holders.

OpenScape UC Application V3
Copyright © 2011 Siemens Enterprise Communications GmbH & Co. KG
Siemens Enterprise Communications GmbH & Co. KG is a Trademark Licensee of Siemens AG
A31003-S5030-U119-3-7619
www.siemens-enterprise.com